

Release Notes for 6200 Switches [1.30](#). [2.29](#). [3.30](#). [4.29](#).

AOS-CX 10.16.xx

- [10.16.1010](#)
- [10.16.1006](#)

The initial release of AOS-CX 10.16.xx is a Long Supported Release (LSR).

- LSRs are long lived releases where Aruba will introduce new features and new hardware, and park hardware (that is, this may be the last major release supported) as needed.
- AubaOS-CX (AOS-CX) LSR support period: Initial Release + 5 year.
- The End of Maintenance (EOM*) and End of Support (EOST) will be the same date.

For more information on this and other active release types, refer to <https://www.arubanetworks.com/support-services/end-of-life/arubaos-software-release/>.

Compatibility/interoperability [1.30](#). [2.29](#). [3.30](#). [4.29](#).

The switch web agent supports the following web browsers:

Browser	Minimum supported versions
Edge (Windows)	41
Chrome (Ubuntu)	76 (desktop)
Firefox (Ubuntu)	113
Safari (MacOS)	12
Safari (iOS)	10 (Version 12 is not supported)

Internet Explorer is not supported.

Recommended versions of network management software for switches found in this release note:

Management software	Recommended version(s)
---------------------	------------------------

NetEdit	Refer to the AOS-CX and NetEdit Compatibility Matrix .
---------	--

HPE Aruba Networking Management Software (AirWave)	8.3.0.4
--	---------

HPE Aruba Networking Central	2.5.8
-------------------------------------	-------

[1.30](#). [2.29](#). [3.30](#). [4.29](#).

HPE Aruba Networking ClearPass Policy Manager	
--	--

[1.30](#). [2.29](#). [3.30](#). [4.29](#).

NOTE: As part of a TLS 1.3 enhancement in AOS-CX 10.16, OpenSSL in CX switches has been upgraded to OpenSSL 3.x. OpenSSL 3.x is only compatible with Clearpass Policy Manager **6.11.0** or later. When using AOS-CX switches running 10.16 with Clearpass Policy Manager version 6.10.x or lower, TLS applications will fail since the OpenSSL version utilized in these lower versions of Clearpass Policy Manager is incompatible with OpenSSL 3.x as per the FIPS standards.

IMC	E0710P03
-----	----------

For more information, see the respective software manuals.

To upgrade software using NetEdit, make sure to upgrade to the above version of NetEdit first and then execute the switch software upgrade on devices discovered by this version of NetEdit. For more information, refer to the [NetEdit Release Notes](#).

Products Supported 1.30. 2.29. 3.30. 4.29.

AOS-CX 10.16.xxxx releases support the 6200 Switch series. The following table lists any applicable minimum software versions required for that model of switch.

If your product is not listed in the following table, no minimum software version is required.

Product Number	Product Name	Minimum Software Version
JL724A	HPE Aruba Networking CX 6200F 24G 4SFP+ Switch	10.04.1000
JL725A	HPE Aruba Networking CX 6200F 24G Class4 PoE 4SFP+ 370W Switch	10.04.1000
JL726A	HPE Aruba Networking CX 6200F 48G 4SFP+ Switch	10.04.1000
JL727A	HPE Aruba Networking CX 6200F 48G Class4 PoE 4SFP+ 370W Switch	10.04.1000
JL728A	HPE Aruba Networking CX 6200F 48G Class4 PoE 4SFP+ 740W Switch	10.04.1000
R8V08A	HPE Aruba Networking CX 6200M 24G 4SFP+ TAA Switch	10.11.1005
R8V09A	HPE Aruba Networking CX 6200M 24G Class4 PoE 4SFP+ TAA Switch	10.11.1005
R8V10A	HPE Aruba Networking CX 6200M 48G 4SFP+ TAA Switch	10.11.1005
R8V11A	HPE Aruba Networking CX 6200M 48G Class4 PoE 4SFP+ TAA Switch	10.11.1005
R8V12A	HPE Aruba Networking CX 6200M 36G 12SR5 Class6 PoE 4SFP+ TAA Switch	10.11.1005
R8V13A	HPE Aruba Networking CX 6200F 12G Class4 PoE 2G/2SFP+ 139W TAA Switch	10.11.1005
R8Q72A	HPE Aruba Networking CX 6200F 12G Class4 PoE 2G/2SFP+ 139W Switch	10.11.1005
R8Q67A	HPE Aruba Networking CX 6200M 24G 4SFP+ Switch	10.11.1005
R8Q68A	HPE Aruba Networking CX 6200M 24G Class4 PoE 4SFP+ Switch	10.11.1005
R8Q69A	HPE Aruba Networking CX 6200M 48G 4SFP+ Switch	10.11.1005
R8Q70A	HPE Aruba Networking CX 6200M 48G Class4 PoE 4SFP+ Switch	10.11.1005
R8Q71A	HPE Aruba Networking CX 6200M 36G 12SR5 Class6 PoE 4SFP+ Switch	10.11.1005
JL724B	HPE Aruba Networking CX 6200F 24G 4SFP+ Switch 4.29.	10.13.0001
JL725B	HPE Aruba Networking CX 6200F 24G Class 4 PoE 4SFP+ 370W Switch 3.30.	10.13.0001
JL726B	HPE Aruba Networking CX 6200F 48G 4SFP+ Switch 2.29.	10.13.0001
JL727B	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP+ 370W Switch 1.30.	10.13.0001
JL728B	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP+ 740W Switch	10.13.0001
S0M81A	HPE Aruba Networking CX 6200F 24G 4SFP Switch	10.13.0001
S0M82A	HPE Aruba Networking CX 6200F 24G Class 4 PoE 4SFP 370W Switch	10.13.0001
S0M83A	HPE Aruba Networking CX 6200F 48G 4SFP Switch	10.13.0001

Product Number	Product Name	Minimum Software Version
S0M84A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP 370W Switch	10.13.0001
S0M85A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP 740W Switch	10.13.0001
S0M86A	HPE Aruba Networking CX 6200F 24G 4SFP+ TAA-compliant Switch	10.13.0001
S0M87A	HPE Aruba Networking CX 6200F 24G Class 4 PoE 4SFP+ 370W TAA-compliant Switch	10.13.0001
S0M88A	HPE Aruba Networking CX 6200F 48G 4SFP+ TAA-compliant Switch	10.13.0001
S0M89A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP+ 370W TAA-compliant Switch	10.13.0001
S0M90A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP+ 740W TAA-compliant Switch	10.13.0001
S0G13A	HPE Aruba Networking CX 6200F 24G 4SFP TAA-compliant Switch	10.13.0001
S0G14A	HPE Aruba Networking CX 6200F 24G Class 4 PoE 4SFP 370W TAA-compliant Switch	10.13.0001
S0G15A	HPE Aruba Networking CX 6200F 48G 4SFP TAA-compliant Switch	10.13.0001
S0G16A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP 370W TAA-compliant Switch	10.13.0001
S0G17A	HPE Aruba Networking CX 6200F 48G Class 4 PoE 4SFP 740W TAA-compliant Switch	10.13.0001



[Back to Top](#)